



SPRINTER 6000 START 230V 12-24V



Overview

SPRINTER 6000 START 230V 12-24V

cod. 829392

Battery charger and starter for charging free electrolyte batteries (WET) with 12/24V voltage and starting all kinds of cars, vans and light trucks. Characteristics: choice of normal charge, quick charge (BOOST), quick start * display of charging and starting current * protection against overloads and polarity reversal.



1 PH 230V



CAR



TRACTOR



SMALL VAN



CE MARKING



EAC CERTIFICATION

Technical data



CODE 829392



MAINS VOLTAGE 230 - 1 ph V50/60Hz



CHARGE/START POWER 2 / 10 kW



CHARGING VOLTAGE 12 / 24 V



EFFECTIVE CHARGING CURRENT 90 A



RATED CHARGE CURR. EN60335-2-29 70 A



START CURRENT 1V/C EN60335-2-29 360 A



MAX STARTING CURRENT 570 A



MIN./MAX RATED REFERENCE CAPACITY 20 / 1550 Ah



ADJUSTMENT POSITIONS 4



DIMENSIONS 32 - 38 - 78 cm(L,W,H)



WEIGHT 24 kg



EAN CODE 800489796192 7



PIECES/PALLET 18 pz/pallet



PIECES/PALLET - B 24 pz/pallet - B

Included Accessories



SPRINTER 6000 START 230V 12-24V



COLORADO 150B WORK CLAMP 150A - 712001



COLORADO 150R POSITIVE CLAMP 150A - 712002